

# Grafic PS5

## Graphics Photopolymer Emulsion

### Applications

General graphic printing.

### Characteristics

- Extremely fast pre-sensitized emulsion (no diazo required), aquamarine color
- Designed for printing solvent-based inks
- High resolution with precise stencil edge sharpness thanks to high solid content (36%)
- Post-exposure optional, not required
- Easy reclaim with standard emulsion removers

### Features/Benefits

- 1-part emulsion replaces 2-part solvent-resistant emulsions with no mixing, no stains, and long shelf life

### Directions for Use

Handle under yellow safelight or low wattage tungsten lights. Avoid exposure to daylight, quartz/halogen lamps, cool white fluorescent lamps or discharge lamps.

### Sensitizing & Mixing

Emulsion is presensitized during production, no mixing required.

### Mesh Preparation & Degreasing

Degrease and abrade new mesh with SAATI Direct Prep 1 in order to optimize stencil adhesion; dry and store the screen in a dust free, dry environment prior to coating. For more applications, thoroughly degrease the mesh prior to use with SAATI Direct Prep 2.

### Coating

**By Hand:** Using a high quality scoop coater or coating trough, apply one or two coats to the substrate side of the screen, followed by one or two coats on the squeegee side. For a thicker stencil, apply additional coats to the squeegee side prior to drying. For a higher quality stencil with a minimal increase in stencil thickness, apply one or two additional coats to the substrate side of the screen after the initial coats have dried.

**With Automatic Coating Machines:** For general purpose printing use 1+2 coating program, with one coat on substrate side and two coats on squeegee side of screen. For thicker stencils apply additional coats on squeegee side by changing machine program to 1+3, 1+4, etc. For a high quality stencil with controlled edge definition, but without excessive emulsion build up (EOM), use 1+1 and then dry screen before applying additional 'wet on dry coats' with 1+1 or 2+2 program, until desired Rz value is attained.

### Drying & Storage

Thoroughly dry the coated screen at a maximum temperature of 104°F (40°C) in a dust free, dark or yellow light area, with the substrate side facing down to optimize stencil quality. Coated screens should be stored in a dust free, dry, safelight environment.

### Exposing

**With Film Positive** – Ensure that all surfaces, emulsion, film and glass are free of dust to minimize pinholes. Contact the emulsion side of the positive with the substrate side of the screen and secure in position before placing the screen in a suitable vacuum frame. Many variables, such as lamp type and age, distance from lamp to screen, mesh type and coating thickness, can affect exposure time. To confirm correct exposure, adhere a SAATI 21-Step Sensitivity Guide to the perimeter of the emulsion outside of the art, but in an area that will be completely exposed. Develop the image with a strong & finely divided water spray applied equally to all areas of the emulsion, including the sensitivity guide. A correct exposure level is indicated by holding 7 solid steps on the sensitivity guide once developing is concluded.

**With Direct to Screen Ink or Wax Mask, or CTS Exposure** – Ensure that the emulsion surface is free of dust to minimize pinholes. To confirm correct exposure, adhere a SAATI 21-Step Sensitivity Guide to the perimeter of the emulsion, outside of the art but in an area of the emulsion that will be completely exposed. Develop the image with a strong & finely divided water spray applied equally to all areas of the emulsion, including the sensitivity guide. A correct exposure level is indicated by holding 6 solid steps on the sensitivity guide once developing is concluded.

### Developing

Wet both sides of the screen with a strong, finely divided spray of water and continue washing out until all image areas are fully open. Rinse both sides of the screen and dry thoroughly before use. A properly exposed and developed screen will not leave residues on the squeegee side.

# Grafic PS5

## Graphics Photopolymer Emulsion

### Post Exposing

Post expose the developed stencil with daylight or an exposure lamp to produce a more water and/or solvent resistant stencil. This is particularly effective process to improve water resistance of SBQ based emulsions for use with water-based inks, or discharge inks for textile printing applications. SAATI Pro-Lite 300 or 450 LED Exposure Lamps are recommended for fast and consistent results with any combination of mesh & emulsion.

### Reclaiming

**Manual Process** - Remove all ink residues immediately after printing with either SAATI Remove IR11 or IR18. Remove stencil with SAATI Remove ER1 or ER2 (concentrates), or Remove ER5. For stains use a second application of SAATI Remove IR11 or IR18, and for stubborn ghost images, use SAATI Remove HR3 or HR9 followed by a pressure washing from bottom to top.

**Automatic Machine Process** - Remove all ink residues immediately after printing with either SAATI Remove IR11 or IR18. Remove stencil with SAATI Remove ER10, ER13, or ER25 (concentrates). For stains use a second application of Remove IR11 or IR18, and for stubborn ghost images, use SAATI Remove HR3 or HR9 followed by a pressure washing from bottom to top.

### Problem Solving

#### Poor Coating Quality

- Properly clean, degrease and rinse the screen to remove all residues and traces of chemicals
- Properly and evenly tension the fabric
- Clean and ensure the scoop coater does not present any defect edge

#### Poor Detail or Difficulty Washing Out Image

- Ensure emulsion and coated screens are handled in safelight conditions only

- Ensure a minimum vacuum of 0.66 bar (500 mmHg or 20 in Hg) on vacuum gauge for optimum contact of the positive
- Optimize exposure time and use only high quality film positives
- Do not store sensitized emulsion or coated screen at high temperatures

#### Emulsion Falls Off, Extreme Pinholes or Severe Stencil Breakdown During Printing

- Ensure that damp screens are not being exposed
- Only expose screens when an even and consistent coating thickness has been confirmed
- Ensure that stencil has not been severely underexposed
- Ensure mixed emulsion is not too old, has been correctly sensitized and has not been stored at high temperature

#### Difficulty Reclaiming Screens

- Not reclaimable once catalyzed
- Optimize exposure time and properly rinse the squeegee side of the screen during developing to remove all residual traces, especially when using higher mesh count dyed fabric

### Health & Safety

Before using, refer to appropriate Safety Data Sheets. Contact SAATI at [info.IT@saati.com](mailto:info.IT@saati.com) to request SDS.

### Storage

When sealed in the original container and stored in cool conditions, SAATI products will maintain their original properties for one year from the date of production.

### Packaging

Available in 0.9, 4.5 and 200 kilogram containers.

### Garanzia e risarcimenti

Le istruzioni, le avvertenze e i dati tecnici contenuti nella presente scheda tecnica costituiscono una guida all'uso del prodotto e non sono vincolanti per la società. Le informazioni contenute nella presente scheda tecnica possono essere soggette a modifica senza obbligo di preavviso. esplicito o implicito di commerciabilità o adeguatezza per un impiego partico

La presente clausola sostituisce tutte le garanzie lare:

Tutti i prodotti liquidi SAATI sono garantiti contro qualsiasi difetto dei materiali e di produzione e corrispondono alle specifiche indicate nelle schede di sicurezza SAATI. SAATI sostituirà o risarcirà il prezzo di qualsiasi prodotto liquido Saatichem non conforme alla presente garanzia entro il periodo di validità di quest'ultima.

In nessun caso SAATI può essere ritenuta responsabile di eventuali perdite o danni diretti e indiretti, compresi senza limitazione i danni casuali, particolari o consequenziali o i costi di materiali o di manodopera derivanti dal recupero o dalla sostituzione di tessuti, telai, inchiostro, supporto grafico finito o qualsiasi altro prodotto.